

Deep Sea - P-8610 Control Panel Kit

Panel Features:

- Dimensions: 15.50" x 11.25" x 10.75"
- Black ABS UV Protected Corrosion Proof Cabinet with Corrosion Resistant Hardware
- Deep Sea DSE8610MKII Auto Start Load Sharing & Synchronizing Module
- 11 inputs, 8 outputs, 4 analog inputs, speed and voltage bias outputs, BUS sensing, GEN sensing, CANBUS, ETHERNET, and MODBUS
- Front panel configurable with external panel mounted USB port
- Panel mounted and programmed pilot relays for: start, run and auxiliary output
- Color coded engine harness with cannon plug
- Color coded generator AC harness exits the bottom of the panel
- Color coded AC bus harness exits the bottom of the panel
- Panel vibration mounts, USB programming cable & electrical schematics included
- Includes a VDO 1/8" NPT Oil Pressure and 3/8" NPT Coolant Sender
- Supplied 85 amp start solenoid shipped loose
- Current Transformers are sold separately

Additional Module Options:

- DSE2157:** Output Expansion Module (8 Form C contacts)
DSE2130: Input Expansion Module (8 inputs)
DSE890: 4G Ethernet Web Gateway (Req. 4G cellular service)
DSE855: Ethernet Module
P6-8-DS: 8 Light Remote Annunciator
P6-16-DS: 16 Light Remote Annunciator



Additional Panel Options:

DS16: 12Vdc additional Aux. Relay 40A

DS17: 24Vdc additional Aux. Relay 30A

DS32: SPDT Toggle Switch

DS40: Alarm Buzzer

DS45B: Generator AC Harness

DS45D: AC Bus Harness

DS67: Emergency Stop Button

DS20: 12Vdc 3PDT 10A Plug-in Form C Relay

DS21: 24Vdc 3PDT 10A Plug-in Form C Relay

DS74: Qty. 1 DS2157-01 Modules



FOR A QUOTE OR TO ORDER PLEASE CONTACT US:

(800)-383-2078 | (386)-274-2079 | www.davidsonsales.com | panelsource@davidsonsales.com